



BCT Technology

We Create High Standard DC to DC switching Power Supply

ATX12V		300W			BCT-A300	
DC Input	12VDC	Input Range			9VDC to 18VDC	
DC Output	+3.3V	+5V	+12V	-12V	-5V	+5VSB
300W	21A	35A	15A	2A	1A	2A
Minimum	0A	3A	1A	0A	0A	0A

▲ Total combined output of +3.3V and +5V should be not exceed 150W

CAUTION!

Do not remove this cover. No serviceable components inside. Trained service people only. Made in Taiwan R.O.C

ATTENTION!

Ne pas ouvrir les couvercles sous aucun pretexte. Reservee au personnel autorise. Il n'y a pas de composants qui puissent etre entretenus par l'utilisateur ou en clientele

VORSICHTIGEFAHRENZONE

Abdeckung Unter Keinen Umstanden Abnehmen!
Es Sind Keine Zu Wartenden Bauteile Enthalten!

MC



Désignation	Alimentation ATX P4, 300 Watts, 12 Volts en entrée (idéale pour matériel embarqué), dimensions : 140 x 150 x 85 mm
Connecteurs	1 ATX 20 pins pour la carte mère 1 ATX 4 points pour les cartes mère Pentium 4 9 pour les périphériques
Dimensions totales	P x l x h = 155 x 150 x 85 mm pour 2,030 kg
Dimensions utiles	P x l x h = 140 x 150 x 85 mm
Dimensions emballage	P x l x h = 210 x 170 x 108 mm pour 2,140 kg
Boîtier	Métal
Garantie	1 an
Comprend	1 alimentation ALIM-300W12V

